

UltraAV 4x4 Matrix Control Codes (Remote 1)

Item	Command	Description
1	SWC <input type="checkbox"/> 1 <input type="checkbox"/> A	Switch output channel 1 to input channel A
2	SWC <input type="checkbox"/> 1 <input type="checkbox"/> B	Switch output channel 1 to input channel B
3	SWC <input type="checkbox"/> 1 <input type="checkbox"/> C	Switch output channel 1 to input channel C
4	SWC <input type="checkbox"/> 1 <input type="checkbox"/> D	Switch output channel 1 to input channel D
5	SWC <input type="checkbox"/> 2 <input type="checkbox"/> A	Switch output channel 2 to input channel A
6	SWC <input type="checkbox"/> 2 <input type="checkbox"/> B	Switch output channel 2 to input channel B
7	SWC <input type="checkbox"/> 2 <input type="checkbox"/> C	Switch output channel 2 to input channel C
8	SWC <input type="checkbox"/> 2 <input type="checkbox"/> D	Switch output channel 2 to input channel D
9	SWC <input type="checkbox"/> 3 <input type="checkbox"/> A	Switch output channel 3 to input channel A
10	SWC <input type="checkbox"/> 3 <input type="checkbox"/> B	Switch output channel 3 to input channel B
11	SWC <input type="checkbox"/> 3 <input type="checkbox"/> C	Switch output channel 3 to input channel C
12	SWC <input type="checkbox"/> 3 <input type="checkbox"/> D	Switch output channel 3 to input channel D
13	SWC <input type="checkbox"/> 4 <input type="checkbox"/> A	Switch output channel 4 to input channel A
14	SWC <input type="checkbox"/> 4 <input type="checkbox"/> B	Switch output channel 4 to input channel B
15	SWC <input type="checkbox"/> 4 <input type="checkbox"/> C	Switch output channel 4 to input channel C
16	SWC <input type="checkbox"/> 4 <input type="checkbox"/> D	Switch output channel 4 to input channel D
17	PWR <input type="checkbox"/> 1	System Power ON
18	PWR <input type="checkbox"/> 0	System Standby
19	RST	System Reset. All channels go back to channel A

Box = Space